


FBXB01C

Step 1





Make wire connections as shown

Step 2



Connect adaptor to 110-220 VAC power supply

Step 3




On transmitter box:

Power (top) GREEN LED glows
 Button (middle) RED :LED is off
 SYNC (bottom) LED blinks for 20sec
 [this transmits ALERT-OFF signal]

On panic alarm button box:

Power (top) GREEN LED glows
 Button (middle) RED :LED is off
 SYNC (bottom) LED BLINKS FOR 20SEC


Step 4



PRESS panic alarm button:

(middle) RED :LED is ON for both panic alarm button and transmitter unit
 SYNC (bottom) LED blinks for 20sec
 [this transmits ALERT-ON signal for 20 sec]

Step 5



RELEASE panic alarm button:

By turning the push button clockwise
 (middle) RED :LED is OFF for both panic alarm button and transmitter unit
 SYNC (bottom) LED blinks for 20sec
 [this transmits ALERT-OFF signal]

FORBIX SEMICON INDIA PVT. LTD.
 Bangalore, India
 Website: <https://www.forbixindia.com>
 +91 9742370190 / +91 9742159846

FORBIX Osäuhing,
 Tallinn, Estonia
 Website: <https://www.forbix.eu>
 +372 880 1510

Email: sales@forbixindia.com

FBXTX701AM : Wireless long range transmitter

Technical specification



Precautions and mounting locations:

- Mounted on the top of door / wall
- Easy mounting with 4 screws to secure it tightly
- IP65 enclosure unit, robust and weatherproof
- For indoor purpose use only
- Keep away from metallic enclosures

Wall mount calling unit:

Enclosure type: IP 65 (color grey)

Size: 190 x 90 x 55 mm

Weight: 350gms

Operating voltage:

110-220VAC/50-60Hz to 12VDC converter adapter supplied.

Unit can also be plugged to any 12V external battery. Active working hours depends on the battery power.

FORBIX SEMICON INDIA PVT. LTD.

Bangalore, India

Website: <https://www.forbixindia.com>

+91 9742370190 / +91 9742159846

FORBIX Osäuhing,

Tallinn, Estonia

Website: <https://www.forbix.eu>

+372 880 1510

Email: sales@forbixindia.com

FBXTX701AM

Long range 1-channel signal transmitter (wall mounted)

Features:

- Single channel long range transmitter (2-3Kms range)
- Can be triggered by panic button or external devices
- Pin 1 and 2 connected: Transmitter sends ON signal
- Pin 1 and 2 disconnected: Transmitter sends OFF signal
- Pin 4 and 5 is internally connected to pin 1 and 2 respectively
The pin connections can be done with an external potential free contactor or panic button
- Pin 3 and 6 is the ground terminal to glow indicators in panic alarm button box
- ON/OFF signals transmits for 10-20 seconds, (depending on the application). SYNC indicator blinks for every transmission packet
- For FBXTX701A transmitter, signal 1 and signal 2 pins are internally connected to each other.(since it is a signal channel transmitter). FBX702A transmitters have independent signal pins

Technical details:

- Transmitter with external PA +28dbm
- Operating frequency: 380 – 480 MHz
- System operates works on signal hop mechanism. Signal transmission happens at more than 12-15 predefined frequencies
- Modulation type: GFSK
- Radio IC: CC1100 (Chipcon/TI) and other equivalents in sub-GHz freq.
- Modulation: GFSK
- Data packet error correction mechanism: FEC

Wiring (color coding)

[1]: channel 1 signal 1 output

[2] : channel 1 loop signal

[3] GND: return path for signal 1 indicator

[4]: internally connected to 1

[5] : internally connected to pin 2

[6] GND

Signal transmissions:

Any change in the input status of PIN [2] or [5] will cause the transmission

Application and features:

- Motor pump controllers
- Conveyor belts ON/OFF switch
- Panic alarm in buildings (in case of emergency)



Model: FBXB01C

Panic alarm button box (latch type)

Features:

- The button box contains a potential free contactor point push button
- It serves as a loopback input mechanism for the transmitter unit
- Power indicator, button press indicator, signal transmission indicator

Signal transmissions:

- 1: signal from transmitter
- 2: loopback signal to transmitter
- 3: (GND) ground terminal
- 4: internally connected to pin 1
- 5: internally connected to pin 2
- 6: (GND) ground terminal

- Press button to activate
- Rotate CLOCKWISE to release the alarm

Application and features:

- Panic alarm in buildings (in case of emergency)
- Motor pump controllers
- Conveyer belts ON/OFF switch
- Wall mount panic button triggers the transmitter and eventually activates a siren alarm at a distant location. The push button alarm connects to a transmitter with a wire cable. The length of the cable should be not more than 8-10 meters

WARNING

**DO NOT ROTATE THE KNOB ANTICLOCKWISE
THIS WILL PERMANENTLY DAMAGE THE BUTTON**

Precautions and mounting locations:

Mounted on the top of door / wall

- Easy mounting with 4 screws to secure it tightly
- IP65 enclosure unit, robust and weatherproof
- For indoor purpose use only
- Keep away from metallic enclosures

Wall mount calling unit:

Size: 150 x 90 x 55 mm

Weight: 200gms

FORBIX SEMICON INDIA PVT. LTD.

Bangalore, India

Website: <https://www.forbixindia.com>

+91 9742370190 / +91 9742159846

FORBIX Osäuhing,

Tallinn, Estonia

Website: <https://www.forbix.eu>

+372 880 1510

Email: sales@forbixindia.com