



Precautions and mounting locations:

- Remotes can be hand operated or mounted on the a door / wall / bed / table or any flat surface
- Easy mounting of remote jacket with 2 screws
- Designed for indoor purpose use only
- Keep away from metallic enclosures
- In the remote controllers, do not connect the battery in opposite direction
- Receiver unit can mount on the wall on keyholes or placed on a flat surface

Physical dimension

Receiver indicator Size: 240 x 165 x 45 mm
Weight: 320 gms
Remote controller size: 120 x 40 x 20 mm
Remote controller weight: 45 gms

Model: FBXA01

Wireless alarm for gated community

Features:

- 6-100 wireless remote controllers
- Signal range 20-30 meters indoors
- Outdoors range 100-200 meters
- 108db loud siren (audible to 200m distance)
- Metal antenna to enhance the range of communication
- Receiver has
 - **RED Beacon light**
 - **Siren sound** around ~90 decibel
 - **Number display** to show the calling remote button
 - Numbers show from 00-99, it is possible to program customized numbers as well
- Remote has 1 red light indicator to indicate button press
- Remote control has 3 buttons
 - **TOP** button: siren continuously ON
 - **BOTTOM** button: siren OFF
 - **CENTER** button to momentarily turn ON the siren

Technical details:

Operating frequency: 315– 480 MHz
System works on signal hop mechanism. Reception happens at more than 12-15 predefined frequencies
Modulation type: GFSK
Radio IC: CC1100 (Chipcon/TI) and equivalents in sub-GHz freq.
Receiver sensitivity: – 112 dbm

Operating voltage:

110-220VAC/50-60Hz to 12VDC converter adapter supplied.
Unit can also be plugged to any 12V external battery. Active working hours depends on the battery power

Remote battery:

Battery model: 23A 12 Volt (DC battery)
Battery life: 2-3 years (depending on usage), Alkaline dry
Battery replaceable, non-rechargeable

Signal transmissions:

Make sure to press a button for at least 2-3 seconds for reliable transmission. This increases the range of communication

Application and features:

- Panic alarm in buildings (in case of emergency)
- Alarm displays for security / gated community
- Alarms for airports, sea harbors, railways, factories and defence forces

FORBIX SEMICON TECHNOLOGIES PVT. LTD.
Bangalore, India
Website: <https://www.forbixindia.com>
+91 974215946 / +91 9742370190

FORBIX Osäuhing,
Tallinn, Estonia
Website: <https://www.forbix.eu>
+372 586 07 111

Email: sales@forbixindia.com