FBXPC02D: Wireless motor pump controller

Technical specification







Motor pump controller Model : FBXPC02



Wireless remote Model : FBX622

FORBIX SEMICON INDIA PVT. LTD.

Bangalore, India

Website: https://www.forbixindia.com +91 9742370190 / +91 9742159846

FORBIX Osaühing, Tallinn, Estonia

Website: https://www.forbix.eu

+372 880 1510

Email: sales@forbixindia.com

Wireless motor pump controller to trigger DOL starter

Model: FBXPC02D

Range of communication:

50 – 60 meters indoors

200 – 400 meters outdoors (line of sight)

Remote controller (hand held):

Battery operated (12VDC), battery type: 23A

Battery life 2-4 years Battery replicable: Yes

Remote controller size:120 x 40 x 20 mm Remote controller weight: 45 gms

Pump controller receiver (wall mount):

Operating voltage: 12VC

(110-220VAC-50/60Hz to 12VDC adapter supplied)

Remote controller size:240 x 140 x 80 mm Remote controller weight: 480 gms

Remote buttons:

Top => to turn ON the pump Bottom => to turn OFF the pump

The radio receiver unit drives the START (green) and STOP (red) button of the DOL starter.

Indicators for pump controller receiver:

Power: GREEN

Sync: BLUE

Remote mode: RED Manual mode: RED Start contactor: YELLOW Motor ON: GREEN

Contactor points:

2 nos. of potential free relay contactor (20Amp) capacity @ 220VAC. Start contactor (momentary ON) to activate the motor start. Start contactor is in parallel connection to the start button of the starter. Second contactor (in series to the stop button) for turning off the motor

Application and features:

Turning motor pump ON/OFF from a distant location

Automation / manual mode of operation

Automatic mode: Remote controller used to turn ON/OFF Manual mode: Existing pump starter used to turn ON/OFF (In manual mode, remote controller signals are bypassed)



DOL (Direct On Line) starter EXISTING wiring MODIFIED wiring Receiver controller AC CONTROLLER P.B. OFF P.B. ON P.B. MAIN CONT. NO MAIN CONT. MAIN CONT. NO MAIN CONT. MAIN CO

