



FBXS02

Wireless 118db siren alarm

Features:

- 118db loud siren
- 1 indicator for power GREEN light
- 1 indicator BLUE SYNC light to check signal reception
- 1 indicator RED for siren ON/OFF selection
- 1 metallic antenna for improving signal reception
- Starts siren on press of panic alarm button
- Stops the indicator on release of panic alarm button
- Long range 380-480MHz wire / rubber duck antenna (+3dbi)
- Compatible with high power transmitters FBX5XX series

Technical details:

Operating frequency: 380 – 480 MHz

System works on signal hop mechanism. Reception happens at more than 12-15 predefined frequencies

Modulation type: GFSK

Radio IC: CC1100 (Chipcon/TI) and equivalents in sub-GHz freq.

Receiver sensitivity: – 112 dbm

Operating voltage:

110-220VAC/50-60Hz to 12VDC converter adapter supplied.

Unit can also be plugged to any 12V external battery. Active working hours depends on the battery power.

Siren alarm (receiver):

Mounted on the top of door of security rooms / guard rooms / office / public places / guest houses / hotel suites etc.

Loud 118db siren sound when panic button is pressed

Application and features:

- Alerts building security or maintenance staff in case of emergency from anywhere inside the building

The range of communication is 100-500 in open line of sight (depending on transmitter PA strength).

Audible distance ~500 meters (or more depending on ambient noise).

Precautions and mounting locations:

- Mounted on the top of door / wall
- Easy mounting with 2 screws keyhole hang
- IP65 enclosure unit, robust and weatherproof
- Keep away from metallic enclosures

Wall mount calling unit:

Enclosure type: IP 65 (color grey)

Size: 250x 90 x 55 mm

Weight: 450gms

FORBIX SEMICON INDIA PVT. LTD.

Bangalore, India

Website: <https://www.forbixindia.com>

+91 9742370190 / +91 9742159846

FORBIX Osäuhing,

Tallinn, Estonia

Website: <https://www.forbix.eu>

+372 880 1510

Email: sales@forbixindia.com